



Firmware update procedure

SMU4000 Series

Products:

SMU4001
SMU4201

The latest firmware updates and Instruction Manuals can be found at www.aimtti.com/support

To update the firmware:

- Download the latest version of the SMU firmware from the website. (This is compatible for both 4001/4201 models).
- Unzip the compressed file.
- In the extracted folder you will find another folder called 'UPDATE'. Copy the 'UPDATE' folder to the root of a FAT32 formatted USB flash drive.
- Insert the USB flash drive in the SMU, the top left icon will turn green,  If the icon turns red, the USB flash drive is not supported.
- Navigate to: CNFG > [System] Manage> [Environment & Upgrade] Firmware Update.
- A pop up will appear asking you to confirm the action, press OK to confirm.
- The firmware update will begin, during the update the unit will restart multiple times.
- Once completed, the Home screen will appear alongside a message to confirm the unit has upgraded successfully.
- The USB flash drive can now be removed.

CAUTION



Do not delete or change any of the files inside the "UPDATE" folder prior to a firmware update.
Do not remove power to the instrument during the update.

In the unlikely event that update fails, the SMU can be put into a recovery mode. See the 'System Management' section of the SMU4000 Instruction Manual for more details.